

CANDELABRA QUICK CONNECT INSTRUCTIONS

TOOLS REQUIRED:

- Needle nose pliers
- Paperclip or needle tool
- Candelabra socket
- Cord
- Candelabra bulb



1) Use pliers to double over the exposed wire for extra strength and security.

2) Once you have doubled over both wires on the cord, twist them until they become tight. Be careful to avoid fraying. Use a paper clip or needle tool to pry open the first connector on the candelabra socket. Insert the wire into the socket and remove the paper clip.



3) Repeat the process using the paper clip with the second connection on the socket, and lightly tug on the cord to ensure the connection is secure.

